GIRA Data sheet

© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

Fan coil actuator for KNX

Specification	Order No.	Packing unit	PS	EAN
DRA	2163 00	1	26	4010337059387

Features

- Fan coil actuator for operation of ventilator convectors (fan coil units), implemented for room air conditioning.
- The actuator receives telegrams, e.g. from a room temperature controller, and converts variable telegrams into equivalent fan speeds and valve positions
- Connection of a ventilator convector with up to six ventilator gradations or connection of two ventilator convectors each with up to three fan speeds with double pipe systems.
- Manual actuation.
- Building site operation: Outputs can be operated manually without bus voltage with operating voltage only.
- Operating modes for heating or cooling, or combined heating and cooling.
- 2-pipe or 4-pipe operation. 2-pipe system uses a shared water circuit for heating and cooling. 4-pipe system consists of separate supply and return line for the heating and cooling system.
- Individual or hierarchic switching of fan speeds.
- Feedback, output indication, block function for each channel, level limitation.
- Behaviour after bus voltage failure or bus/mains voltage failure and following an ETS programming process can be configured.
- Limit values can be set.
- Cyclical or event-oriented transmission.
- Free channels can be used for switching functions, e.g. for room lighting.

Technical data

KNX medium: TP256

Switching contact: μ contact, 1 x zero-voltage NO contact

Breaking capacity 230 V AC: 10 A / AC1 or 10 A / AC3

Maximum switch-on current

- 200 μs: 800 A - 20 ms: 165 A

Connected load

- Ohmic load: 2300 W

- Capacitive load 230 V AC: 10 A, max. 140 μF

Light bulbs: 2300 W
HV halogen lamps: 2300 W
Wound electronic transformer: 1200 VA

GIRA Data sheet

catalogue.gira.com

© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

- Tronic transformer:	1500 W
- Fluorescent lamps, uncompensated:	1000 VA
- Fluorescent lamps,lead-lag circuit:	2300 VA
- Fluorescent lamps, parallel-compensated:	1160 VA
- Mercury-vapour lamps, uncompensated:	1000 W
- Mercury-vapour lamps, parallel-	1160 W
compensated:	

Connections

- KNX: Connection and junction terminal

- Load: Screw terminals

Connection cross section: Max. 4 mm²

Notes

- VDE approval in accordance with EN 60669-1, EN 60669-2-1.
- Installation on DIN top-hat rail.

Scope of supply

- Connection and junction terminal for KNX included with delivery.

Dimensions

Modular width (MW): 4