© Copyright by catalogue.gira.com Gira Giersiepen GmbH & Co. KG

All rights reserved www.gira.com

**Motion detector Cube 120** 

**GIRA** Data sheet

Specification	Order No.	Packing unit	£/piece without VAT	PS	EAN
pure white glossy	2442 02	1	115.75	08	4010337056430
anthracite	2442 10	1	121.01	08	4010337056416

# **Features**

- Automatically switches lighting on/off, depending on thermal motion and ambient brightness.
- Automatic temperature-compensated sensor sensitivity.
- Continuous light (max. 2 h) can be activated using an optional switch/button.
- Test mode for evaluating the detection range.
- Individual adaptation of the detection range using the enclosed covering panel that can be cut to size.
- Adjustable switch-off delay: 5 s to 15 min or short-term operation of 1 s.
- Save current twilight value using teach-in function.
- Glare protection, brightness-independent sensor evaluation for 60 s in the event of glare caused by extraneous light.
- Short-time operation, output is switched on for approx. 1 s.
- Remote control optional.

## **Technical data**

Rated voltage: AC 230 V~, 50/60 Hz

Connected load

- HV LED lamps: typically 200 W 2000 W - Light bulbs:

- Fluorescent lamps, uncompensated: 1000 VA ( $\cos \phi = 0.5$ ) 500 W (45.6 μF) - Fluorescent lamps, parallel-compensated: - Fluorescent lamps, series-compensated: 900 W

Capacitive load: 176 µF

Brightness value

- Brightness value: 2 to 1000 lx

Setting controller

- Delay time: 5 seconds to 15 minutes

# **GIRA** Data sheet

catalogue.gira.com

© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

Connection cross section

Single-wire: Max. 2.5 mm²
Fine-wire without core jacket: Max. 2.5 mm²
fine-wire with core jacket: Max. 1.5 mm²

Protection level: IP54

Ambient temperature: -25 °C to +55 °C

Angle of detection: 120°

Mounting height 2.50 m

- Detection range facing forwards, max.: approx. 16 m - Range at each side, max.: approx. 11 m

#### Notes

- Suitable for ceiling and wall mounting indoors and outdoors.
- Optional: Can be controlled remotely using IR remote control PIR 3.
- Observe high peak switch-on currents with "energy saving lamps". Check suitability of the lamps before use!

# Scope of supply

- Covering panel for adapting the detection range is included with delivery.

### Dimensions in mm

without lens: 87 85