catalogue.gira.com

© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

Weather sensor with weather control unit for KNX

GIRA Data sheet

Specification	Order No.	Packing unit	£/piece without VAT	PS	EAN
	5146 00	1	581.79	06	4010337124405

Features

- The components of the weather station consisting of a weather sensor and a weather control unit cannot be used individually.
- The weather sensor has the following sensors:
- Brightness from three directions (at 90° intervals to each other, compass directions: east, south, west)
- Temperature
- Wind speed
- Precipitation sensor, with integrated heating
- The weather sensor sends the sensor values to the weather control unit, which evaluates the sensor information and sends it to the KNX
- The weather sensor can communicate with up to 20 weather control units (5147 00).
- 10 sensor channels for wind, precipitation, temperature and brightness. Logical AND/OR links can be created within the sensor channels to evaluate multiple sensor values together.
- Evaluation delay for all sensors to ensure reliable functionality.
- 8 sun protection channels for 8 facades with automatic sun protection function incl. evaluation delay to ensure a reliable sun protection
- 2 objects for external brightness sensors.
- Pre-defined day/night object for switchover between day/night mode incl. separate activation/deactivation function via the communication
- Communication object that provides information about any communication problems between the weather control unit and the weather sensor.

Technical data

Weather sensor

- Operating voltage of ext. power supply: DC 18 - 34 V - Internal consumption: max. 5 W

- Connection between weather sensor and 0.6 to 0.8 mm (bus line e.g. J-Y(St)Y 2 x 2 x 0.8)

weather control unit:

Spring plug-in terminal and connection terminal - Connection type:

- Mounting type: Wall or mast mounting

IP44 - Protection class: Ш - Protection class: 0.8 kV - Rated surge voltage: -20 °C to +55 °C - Ambient temperature:

- Wind measuring range: 2 to 30 m/s

GIRA Data sheet

catalogue.gira.com

© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

- Brightness measuring range: 1 to 100,000 lux - Temperature measuring range: -30 °C to +60 °C - Dimensions in mm: W 121 H 105 D 227

Weather control unit

- KNX medium:

KNX rated voltage:Internal consumption:

KNX connection:Maximum cable length between weather

- Maximum cable length between wea sensor and weather control unit:

- Protection class:
- Protection class:

Rated surge voltage:Number of weather control units that can be connected to a weather sensor:

- Ambient temperature:

TP256

DC 21 to 32 V SELV

max. 0.5 W

0.6 to 0.8 mm (bus line e.g. J-Y(St)Y 2 x 2 x 0.8)

1,000 m

IP20 III 0.8 kV 20

-5 °C to +45 °C

Notes

- KNX Data Secure compatible.
- Prepared for Gira One.

Scope of supply

- Connection and junction terminal for KNX included with delivery.

Dimensions

Modular width (MW):

3