GIRA Data sheet

© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

Weather sensor with weather control unit for KNX

Specification	Order No.	Packing unit	£/piece without VAT	PS	EAN
	5146 00	1	581.79	06	4010337124405

Features

- The components of the weather station consisting of a weather sensor and a weather control unit cannot be used individually.
- The weather sensor has the following sensors:
- Brightness from three directions (at 90° intervals to each other, compass directions: east, south, west)
- Temperature
- Wind speed
- Precipitation sensor, with integrated heating
- The weather sensor sends the sensor values to the weather control unit, which evaluates the sensor information and sends it to the KNX bus.
- The weather sensor can communicate with up to 20 weather control units (5147 00).
- 10 sensor channels for wind, precipitation, temperature and brightness. Logical AND/OR links can be created within the sensor channels to evaluate multiple sensor values together.
- Evaluation delay for all sensors to ensure reliable functionality.
- 8 sun protection channels for 8 facades with automatic sun protection function incl. evaluation delay to ensure a reliable sun protection function.
- 2 objects for external brightness sensors.
- Pre-defined day/night object for switchover between day/night mode incl. separate activation/deactivation function via the communication object.
- Communication object that provides information about any communication problems between the weather control unit and the weather sensor.

Technical data

Weather sensor

Operating voltage of ext. power supply:
 Internal consumption:
 DC 18 – 34 V
 max. 5 W

- Connection between weather sensor and 0.6 to 0.8 mm (bus line e.g. J-Y(St)Y 2 x 2 x 0.8)

weather control unit:

- Connection type: Spring plug-in terminal and connection terminal

- Mounting type: Wall or mast mounting

- Protection class:
- Protection class:
- Rated surge voltage:
- Ambient temperature:
- Wind measuring range:
- 20 °C to +55 °C
- 20 °C to +55 °C

Illustrations are similar and may deviate from originals. Prices valid for United Kingdom with prices valid 01/20.

GIRA Data sheet

catalogue.gira.com

© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

- Brightness measuring range: 1 to 100,000 lux - Temperature measuring range: -30 °C to +60 °C - Dimensions in mm: W 121 H 105 D 227

Weather control unit

- KNX medium:

KNX rated voltage:Internal consumption:

- KNX connection:

- Maximum cable length between weather

sensor and weather control unit:
- Protection class:

Protection class: Rated surge voltage: Number of weather control units that can

- Number of weather control units that car be connected to a weather sensor:

- Ambient temperature:

0.6 to 0.8 mm (bus line e.g. J-Y(St)Y 2 x 2 x 0.8) 1,000 m IP20

TP256

max. 0.5 W

DC 21 to 32 V SELV

0.8 kV 20

-5 °C to +45 °C

Notes

- KNX Data Secure compatible.
- Prepared for Gira One.

Scope of supply

- Connection and junction terminal for KNX included with delivery.

Dimensions

Modular width (MW):

3