catalogue.gira.com

GIRA Data sheet

© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

Add-on module for built-in speaker

Specification	Order No.	Packing unit	PS	EAN	
	1259 00	1	18	4010337259008	

Features

- Up to twelve mechanical bell buttons can be connected.
- Additional bell buttons can be connected via additional add-on modules.
- Up to eleven add-on modules can be connected to one built-in speaker.
- Alternating current polling of the bell button connections to prevent oxidation on the button contacts.
- Compact size.
- Securing of connection terminals against incorrect connection.
- Attachment of the add-on module with screws or gluing.

Technical data

Connections

Mech. Bell button:
Common earth of bell buttons:
Connection cable:
12 x screw terminal
1 x screw terminal
2 x connector strip

Protection class: IP44

Ambient temperature: -25 °C to +70 °C

Dimensions

- incl. fixing lug: W 67 x H 66.4 x D 27 mm - without fixing lug: W 67 x H 56 x D 27 mm

Notes

- Module for extension of the built-in speaker when more than eight mechanical bell buttons are to be connected.
- This component enables door communication systems with up to 140 audio devices to be set up (e.g. 1 x built-in speaker, 11 x add-on modules for built-in speakers, 136 x surface-mounted home stations).
- Protection type IP44 only in combination with a suitable front or when installed.

GIRA Data sheet

catalogue.gira.com

© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

Sco	nα	٥f	em	nı	nl	h
360	he	UI	Su	νі	וע	v

- The mounting materials are included with delivery.