catalogue.gira.com

GIRA Data sheet

© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

Cut-off relay, 2-gang

Specification	Order No.	Packing unit	£/piece without VAT	PS	EAN
Flush mounted	0382 00	1/5	76.76	02	4010337382003

Features

- Simultaneous control of more than one blind drive.
- In each case, two drives are electrically decoupled with one cut-off relay.
- With two auxiliary inputs for the individual operation of the blinds and a central input for a central function, e.g. of a timer or for implementation of central control systems in the event of distribution among several RCCBs.

Technical data

Rated voltage: AC 230 V, 50 Hz

Switching current: 4 A, $\cos \phi \ge 0.8$ ind., 100% switch-on duration

Connections

- Power supply: 2 x screw terminal
- Central: 2 x screw terminal
- Drive 1, 2: 2 screw terminals each
- Auxiliary unit 1, 2: 1 screw terminal each

Ambient temperature: -25 °C to +70 °C

Installation depth: 21.5 mm

Notes

- The flush-mounted cut-off relay is installed in a device box (Using a deep device box is recommended.)