#### catalogue.gira.com

**GIRA** Data sheet

© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

# Cut-off relay, 2-gang

| Specification | Order No. | Packing unit | £/piece<br>without VAT | PS | EAN           |
|---------------|-----------|--------------|------------------------|----|---------------|
| DRA           | 0861 00   | 1            | 87.71                  | 02 | 4010337861003 |

#### **Features**

- Simultaneous control of more than one blind drive.
- In each case, two drives are electrically decoupled with one cut-off relay.
- With two auxiliary inputs for the individual operation of the blinds and a central input for a central function, e.g. of a timer or for implementation of central control systems in the event of distribution among several RCCBs.

### Technical data

Rated voltage: AC 230 V, 50 Hz

Switching current: 4 A,  $\cos \phi \ge 0.8$  ind., 100% switch-on duration

Connections

- Power supply: 2 x screw terminal
- Central: 2 x screw terminal
- Drive 1, 2: 2 screw terminals each
- Auxiliary unit 1, 2: 1 screw terminal each

Ambient temperature: -25 °C to +70 °C

#### Notes

- The DRA cut-off relay is installed on a cap profile rail.

## **Dimensions**

Modular width (MW): 2.5