GIRA Data sheet

© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

Add-on module for built-in speaker

Specification	Order No.	Packing unit	£/piece without VAT	PS	EAN
	1259 00	1	101.87	18	4010337259008

Features

- Up to twelve mechanical bell buttons can be connected.

- Additional bell buttons can be connected via additional add-on modules.

- Up to eleven add-on modules can be connected to one built-in speaker.

- Alternating current polling of the bell button connections to prevent oxidation on the button contacts.

- Compact size.

- Securing of connection terminals against incorrect connection.

- Attachment of the add-on module with screws or gluing.

Technical data

Connections - Mech. Bell button: - Common earth of bell buttons: - Connection cable:	12 x screw terminal 1 x screw terminal 2 x connector strip
Protection class:	IP44
Ambient temperature:	-25 °C to +70 °C
Dimensions - incl. fixing lug: - without fixing lug:	W 67 x H 66.4 x D 27 mm W 67 x H 56 x D 27 mm

Notes

- Module for extension of the built-in speaker when more than eight mechanical bell buttons are to be connected.

- This component enables door communication systems with up to 140 audio devices to be set up (e.g. 1 x built-in speaker, 11 x add-on modules for built-in speakers, 136 x surface-mounted home stations).

- Protection type IP44 only in combination with a suitable front or when installed.

catalogue.gira.com

GIRA Data sheet

© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

Scope of supply

- The mounting materials are included with delivery.