catalogue.gira.com

© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

Emergency set System 55

GIRA Data sheet

Specification	Order No.	Packing unit	£/piece without VAT	PS	EAN
pure white glossy	2914 03	1	286.69	34	4010337067900

Features

- Call module with red LED signal light, integrated zero-voltage contact, optionally switchable buzzer (continuous tone) and the option of setting a flashing light or continuous light.
- Pull-cord button with 2.5 m long pull cord with red handle and reassurance light in the button housing, suitable for wall and ceiling mounting.
- Switch-off button with green switch-off key.
- Flush-mounted power supply unit 250 mA.
- The call set can be optionally upgraded with a duty room unit with an integrated sound generator for acoustic call signalling, green presence button with presence light, and yellow buzzer switch-off button.

Technical data

Power supply

- Input voltage: AC 100 to 240 V, 50 to 60 Hz

- Input current: 180 mA
- Output voltage: DC 24 V
- Output current: 250 mA

Ambient temperature: + 5 °C to + 40 °C

Length of pull cord: 2.5 m

Installation: Device boxes

Notes

- For installation in accordance with DIN VDE 0834, use an uninterruptible power supply.
- The components for upgrading the emergency set can be purchased individually.