

**Pushbutton sensor 3 Basis, 2-gang (1+1) for KNX
with start-up rocker**

| Specification | Order No. | Packing unit | £/piece without VAT | PS | EAN |
|---------------|-----------|--------------|------------------------|----|---------------|
| | 5112 00 | 1 | 102.83 | 06 | 4010337086819 |

Features

- Installation on bus coupler 3.
- Safeguarded from disassembly because it is screw-fastened.
- Rocker function: Switching, dimming, blind, value transmitter 1-byte, and scene auxiliary unit.
- White operating LED.
- Two red status LEDs per operating surface.
- Inscription space illumination for rocker sets with inscription space.
- Function of inscription space illumination and status LED can be configured.

Technical data

| | |
|----------------------|-----------------|
| KNX medium: | TP256 |
| Ambient temperature: | -5 °C to +45 °C |
| Protection class: | III |

Notes

- Professional inscription by the Gira inscription service www.marking.gira.com.
- The pushbutton sensor is delivered with a program-neutral start-up rocker. The suitable rocker set for the switch range must be ordered separately.

Scope of supply

- Plain inscription labels included.