GIRA Data sheet

© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

eNet wireless energy sensor, 4-gang

Specification	Order No.	Packing unit	£/piece without VAT	PS	EAN
DRA	5473 00	1	274.78	42	4010337774372

Features

- The eNet radio energy sensors enable the radio transmission of voltage, electricity, and energy values to the eNet server.

- Logging electricity and voltage of the connected device.

- Calculation of effective output, reactive power, apparent power, and active electrical energy.

- Event- or time-controlled transmission of measurement value telegrams to the eNet server.

- Time synchronisation using the eNet server.

Technical data

Rated voltage:	AC 230 V, 50/60 Hz		
Ambient temperature:	-5 °C to +45 °C		
Measurement range - Electricity: - Electrical power: - Energy consumption:	0 mA to 16 A 0 to 3680 W 0 to 99999 kWh		
Wireless frequency:	868.3 MHz		
Range (free field):	approx. 100 m		
Rated load current:	16 A		
Connection cross section:	Max. 4 mm ²		
Length of the data line:	Max. 3 m		

GIRA Data sheet

© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

Notes

- An eNet server is required to operate this DIN rail adapter.

Dimensions

Modular width (MW):

4