catalogue.gira.com

GIRA Data sheet

© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

eNet wireless energy sensor, 4-gang

Specification	Order No.	Packing unit	£/piece without VAT	PS	EAN
DRA	5473 00	1	274.78	42	4010337774372

Features

- The eNet radio energy sensors enable the radio transmission of voltage, electricity, and energy values to the eNet server.
- Logging electricity and voltage of the connected device.
- Calculation of effective output, reactive power, apparent power, and active electrical energy.
- Event- or time-controlled transmission of measurement value telegrams to the eNet server.
- Time synchronisation using the eNet server.

Technical data

Rated voltage: AC 230 V, 50/60 Hz

Ambient temperature: -5 °C to +45 °C

Measurement range

Electricity: 0 mA to 16 A
Electrical power: 0 to 3680 W
Energy consumption: 0 to 99999 kWh

Wireless frequency: 868.3 MHz

Range (free field): approx. 100 m

Rated load current: 16 A

Connection cross section: Max. 4 mm²

Length of the data line: Max. 3 m

GIRA Data sheet

catalogue.gira.com

© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

Notes				
- An eNet server is required to operate this DIN rail adapter.				
Dimensions				
Modular width (MW):	4			